

Type	Device	Input Channel	Sample Rate	Bit Depth	Buffer Size	Measured RTL (ms)	Reported Input Latency	Reported Output Latency	Reported RTL	Measured RTL
ASIO	Roland Rubix 24	IN1	48000	32	80	9.208	223	222	445	442
ASIO	Roland Rubix 24	IN1	48000	32	144	11.458	271	270	541	550
ASIO	Roland Rubix 24	IN1	48000	32	288	21.479	511	510	1021	1031
ASIO	Audient EVO 4	Mic Line Instrument 1	48000	32	32	4.896	107	123	230	235
ASIO	Audient EVO 4	Mic Line Instrument 1	48000	32	64	5.562	139	123	262	267
ASIO	Audient EVO 4	Mic Line Instrument 1	48000	32	128	9.917	251	219	470	476
ASIO	Audient EVO 4	Mic Line Instrument 1	48000	32	256	18.562	475	411	886	891
ASIO	Presonus Studio USB ASIO Driver	Mic/Inst 1	48000	32	32	5.146	103	119	222	247
ASIO	Presonus Studio USB ASIO Driver	Mic/Inst 1	48000	32	64	5.729	135	119	254	275
ASIO	Presonus Studio USB ASIO Driver	Mic/Inst 1	48000	32	128	10.167	247	215	462	488
ASIO	Presonus Studio USB ASIO Driver	Mic/Inst 1	48000	32	256	18.708	471	407	878	898
ASIO	MOTU M Series Safe Mode	In 1	48000	32	32	5.167	59	187	246	248
ASIO	MOTU M Series Safe Mode	In 1	48000	32	64	6.812	91	235	326	327
ASIO	MOTU M Series Safe Mode	In 1	48000	32	128	10.833	155	363	518	520
ASIO	MOTU M Series Safe Mode	In 1	48000	32	256	16.188	283	491	774	777
ASIO	MOTU M Series Safe Mode	In 1	48000	32	512	26.812	539	747	1286	1287
ASIO	MOTU M Series	In 1	48000	32	32	4.167	59	139	198	200
ASIO	MOTU M Series	In 1	48000	32	64	6.167	91	203	294	296
ASIO	MOTU M Series	In 1	48000	32	128	10.146	155	331	486	487
ASIO	MOTU M Series	In 1	48000	32	256	15.479	283	459	742	743
ASIO	MOTU M Series	In 1	48000	32	512	26.188	539	715	1254	1257
ASIO	ZenGo SC ASIO Driver Safe Mode	IN 2	48000	32	32	4.896	104	120	224	235
ASIO	ZenGo SC ASIO Driver Safe Mode	IN 2	48000	32	64	5.583	136	120	256	268
ASIO	ZenGo SC ASIO Driver Safe Mode	IN 2	48000	32	128	8.896	200	216	416	427
ASIO	ZenGo SC ASIO Driver Safe Mode	IN 2	48000	32	256	14.583	328	360	688	700
ASIO	ZenGo SC ASIO Driver Safe Mode	IN 2	48000	32	512	25.917	584	648	1232	1244
ASIO	ZenGo SC ASIO Driver	IN 2	48000	32	32	3.896	104	72	176	187
ASIO	ZenGo SC ASIO Driver	IN 2	48000	32	64	4.562	136	72	208	219
ASIO	ZenGo SC ASIO Driver	IN 2	48000	32	128	6.896	200	120	320	331
ASIO	ZenGo SC ASIO Driver	IN 2	48000	32	256	11.562	328	216	544	555
ASIO	ZenGo SC ASIO Driver	IN 2	48000	32	512	20.896	584	408	992	1003
ASIO	ZOOM UAC-2 ASIO Driver	In 1	48000	32	32	3.708	32	145	177	178
ASIO	ZOOM UAC-2 ASIO Driver	In 1	48000	32	64	5.021	64	177	241	241
ASIO	ZOOM UAC-2 ASIO Driver	In 1	48000	32	128	7.708	128	241	369	370
ASIO	ZOOM UAC-2 ASIO Driver	In 1	48000	32	256	13.042	256	369	625	626
ASIO	ZOOM UAC-2 ASIO Driver	In 1	48000	32	512	23.708	512	625	1137	1138
ASIO	Yamaha Steinberg USB ASIO	UR22mkII Input 1	48000	32	32	5.771	118	166	284	277
ASIO	Yamaha Steinberg USB ASIO	UR22mkII Input 1	48000	32	64	9.125	198	246	444	438
ASIO	Yamaha Steinberg USB ASIO	UR22mkII Input 1	48000	32	128	13.833	310	358	668	664
ASIO	Yamaha Steinberg USB ASIO	UR22mkII Input 1	48000	32	256	20.146	438	534	972	967
ASIO	Yamaha Steinberg USB ASIO	UR22mkII Input 1	48000	32	512	33.771	742	886	1628	1621
ASIO	Yamaha Steinberg USB ASIO low lat	UR22mkII Input 1	48000	32	32	4.833	118	118	236	232
ASIO	Yamaha Steinberg USB ASIO low lat	UR22mkII Input 1	48000	32	64	7.125	150	198	348	342
ASIO	Yamaha Steinberg USB ASIO low lat	UR22mkII Input 1	48000	32	128	10.812	262	262	524	519
ASIO	Yamaha Steinberg USB ASIO low lat	UR22mkII Input 1	48000	32	256	17.167	390	438	828	824
ASIO	Yamaha Steinberg USB ASIO low lat	UR22mkII Input 1	48000	32	512	29.812	694	742	1436	1431
ASIO	Darkglass USB Audio Device	Instrument Raw	48000	32	16	7.208	88	120	208	346
ASIO	Darkglass USB Audio Device	Instrument Raw	48000	32	32	7.542	104	120	224	362
ASIO	Darkglass USB Audio Device	Instrument Raw	48000	32	64	8.417	136	120	256	404
ASIO	Darkglass USB Audio Device	Instrument Raw	48000	32	128	11.583	200	216	416	556
ASIO	Darkglass USB Audio Device	Instrument Raw	48000	32	256	17.042	328	360	688	818
ASIO	Darkglass USB Audio Device	Instrument Raw	48000	32	512	28.292	584	648	1232	1358
ASIO	Solid State Logic ASIO Driver	Input 1	48000	32	16	5.021	88	72	160	241
ASIO	Solid State Logic ASIO Driver	Input 1	48000	32	32	6.104	104	72	176	293
ASIO	Solid State Logic ASIO Driver	Input 1	48000	32	64	6.896	136	72	208	331
ASIO	Solid State Logic ASIO Driver	Input 1	48000	32	128	9.479	248	120	368	455
ASIO	Solid State Logic ASIO Driver	Input 1	48000	32	256	16.396	472	216	688	787
ASIO	Solid State Logic ASIO Driver	Input 1	48000	32	512	25.479	728	408	1136	1223
ASIO	Solid State Logic ASIO Driver SM	Input 1	48000	32	16	6.271	88	120	208	301
ASIO	Solid State Logic ASIO Driver SM	Input 1	48000	32	32	7.104	104	120	224	341
ASIO	Solid State Logic ASIO Driver SM	Input 1	48000	32	64	7.396	136	120	256	355
ASIO	Solid State Logic ASIO Driver SM	Input 1	48000	32	128	11.479	248	216	464	551
ASIO	Solid State Logic ASIO Driver SM	Input 1	48000	32	256	20.396	472	408	880	979
ASIO	Solid State Logic ASIO Driver SM	Input 1	48000	32	512	30.354	728	600	1328	1457

[illegible]